## Round Cut-in Floor Box Kits



## Flush-to-Floor Installation in Existing Wood and Concrete Floors





 Using a 4" diameter hole saw, cut opening in floor approximately 1/2" deep, taking care to avoid structural framing members.



4 Wire receptacle. Install in box.



2 Next, use a 3-1/2" hole saw to cut through the remaining flooring/ subfloor, creating a shelf at the desired depth for the box. Remove material that remains between the saw cuts.



5 Attach plastic gasket support plate to receptacle with #6 x 1/2" screw. Install gasket.

3 Pull cable. Install in box with supplied cable connector. Attach box to floor with (3) #6 x 1-1/4" wood screws (not supplied) through the U-shaped cut outs in the box flange.



6 Attach cover to box with (3) #8 x 1/2" flat head machine screws.

Arlington's round, cut-in **FLOOR BOX KITS** offer installers the low cost, *convenient* way to install a duplex receptacle *flush with the floor*.

The 3.5" round, UL Listed non-metallic floor box is easy to install in an *existing* wood or concrete floor. Electrical conduit must be accessible from underneath the floor if installing in existing concrete.


Hide miscut flooring, cover the edges

of cut carpet and get a neater finish with an **oversized ring** or **carpet ring** to match your cover.

Complete the job with a round 4" **metal cover** in brass or nickelplated brass.

> Floor Box Kit with brass cover FLB3520MB







1 Stauffer Industrial Park Scranton, PA 18517 800/233.4717 Fax 570/562.0646 www.aifittings.com

## Round Metal Cover • Easy to Install in Existing Floor



CATALOG NUMBER	UPC/DCI/NAED MFG. #018997	DESCRIPTION FINISH/COLOR, COVER STYLE	UNIT PKG	STD PKG
FLB3500	00733	3.5" Non-metallic <b>ROUND CUT-IN BOX</b> for Existing Wood or Concrete Floors	4	4
FLOOR BOX	KITS WITH META	L COVERS		
FLB3520MB	00734	FLOOR BOX KIT Round cut-in box, Brass cover w threaded plugs	1	1
FLB3520NL	00735	FLOOR BOX KIT Round cut-in box, NIckel-plated Brass cover w threaded plugs	1	1
FLB3520MB	and FLB3520NL F	LOOR BOX KITS include non-metallic box, round metal cover,		
non-metallic g	asket support plate,	gasket, UL Listed 15 amp TR duplex receptacle, NM94 and NM95 cable connectors,		
(3) #8 x 1/2" fl	at head screws and	(1) #6 x 1/2" screw.		











FLB3520MB

brass cover



TRIM KITS ROUND METAL COVER WITH THREADED PLUGS, GASKETS, 15 AMP DUPLEX TR RECEPTACLE									
FLB3520MBTK	00736	COVER TRIM KIT 4" Round, BRASS	1	1					
FLB3520NLTK	00737	COVER TRIM KIT 4" Round, NICKEL-PLATED BRASS	1	1					








## Arlington

1 Stauffer Industrial Park Scranton, PA 18517 800/233.4717 Fax 570/562.0646 www.aifittings.com



Patents pending FLB3520 0715/25M



Distributed by